



How to Use Spy Feature

Version 1.0

Yeastar Information Technology Co. Ltd

Introduction

MyPBX allows extension to monitor/barge in other conversation. Once this feature is enabled, the extension has the ability to monitor/barge in other calls using the feature codes for each spy mode, refer to 'Feature Codes' page for more information.

Spy modes

1. **General spy:** you have the permission to use the following 3 modes.
2. **Normal spy:** you can only hear the call, but can't talk. Feature code: *90
3. **Whisper spy:** you can hear the call, and can talk with the monitored extension. Feature code: *91
4. **Barge spy:** you can hear the call and talk with them both. Feature code: *92

Note: Spy feature is working for analog extensions as well.

The screenshot shows the 'Edit Extension - 601' window with the 'Other Settings' tab selected. The 'Spy Settings' section is expanded, and the 'Spy Modes' dropdown menu is open, displaying the following options:

- General Spy
- Normal Spy
- Whisper Spy
- Barge Spy

Other visible settings include:

- Other Options:** Call Waiting (unchecked), DND (unchecked), User Web Interface (checked), Ring Out: 30
- Follow me:** Always (unchecked), No answer (checked), When Busy (checked), Transfer to: Voicemail (selected), Number (empty)
- Volume Settings:** Rxgain: 40%, Txgain: 40%
- Mobility Extension:** Enable Mobility Extension (unchecked), Mobility Extension Number: (empty)
- Allow Being Spied:** (unchecked)

Buttons for 'Save' and 'Cancel' are visible at the bottom.

How to Use Spy Feature

Here we give you an example of how to use spy feature.

Use **Extension 100** to monitor the calls of **Extension 101**.

Step1. Enable “Allow Being Spied” in Extension 301 only.

In this case, Extension 301 is allowed to be spied by other extensions.

The screenshot shows the 'Edit Extension - 301' window with the 'Other Settings' tab selected. The 'Allow Being Spied' checkbox is checked and highlighted with a red box. The 'Spy Modes' dropdown is set to '-----'. Other settings include 'User Web Interface' checked, 'Ring Out' set to 30, and 'Follow me' options for 'No answer' and 'When Busy' checked.

Figure 1 Allow be Spied

Note: If “Allow Being Spied” is not enabled, it’s impossible for other extensions to monitor this extension, even they have chosen the “spy modes”.

Step2. Choose the spy modes for Extension 300

In this case, Extension 300 has the right to use the feature code to monitor Extension 301.




Figure 2 Choose Spy Mode

If 300 choose "Normal Spy", it should dial '*90301' to start monitoring;

If 300 choose "Whisper Spy", it should dial '*91301' to start monitoring;

If 300 choose "Barge Spy", it should dial '*92301' to start monitor;

If 300 choose "General Spy", it can dial '*90301', '*91301' or '*92301' to start monitor.

Note: You can dial 'feature code+301' to join the monitor status, when there is an incoming call arriving in 301, you can get the audio immediately.

[The End]